



gosund




### Wifi Smart Switch

Any problems please follow Gosund  
on  and consult the service staff

## ►What's in the Box


Smart switch  
User Manual

## ► At a Glance



-2-

---> Confirm the light status on your plug and follow the App guide.  
( If you don't see blue light quickly blinking,press On/Off button to reset.)  
---> Set a unique name for this smart switch, choose the room location.



-10-

## ►Parameters

Input: 100-240V~, 50/60Hz  
Output: 10A Max  
Wi-Fi: IEEE802.11 b/g/n


NOTE: Press the ON/OFF button to restore the factory setting if you want to erase the switch's current settings.

## ► Connection diagram



-3-

B: AP Mode(Indicator light blinks once every 2 seconds ) If the Easy mode connection failed, please remove and install the smart switch into your power outlet again. When you make sure the indicator light is quickly blink again for Easy mode, hold the power button for about 7seconds to switch to AP mode.



-11-

## ►Indicator Light Status


Blue light blinks every 0.5 second-Easy Mode connection  
Blue light blinks every 2 seconds- AP Mode connection  
Red light- Power is ON  
No light- Power is OFF

## ►Install the "Gosund" App

1. Search for Gosund App on App store/Google Play Store, or just scan the QR code below to download.(For iPhone, you can use build-in camera to scan the

-4-

Once you see the indicator light slowly blink(every 7 seconds ), you can start to try the AP mode connection.  
---> First go back to the Add Device "+" interface, choose the AP Mode on the upper right corner.



-12-

QR code. For Android, you may need barcode scanner to do that.

Please confirm the App icon before downloading.)

PS: You can also add this smart switch to smart life app directly if you already have it on your phone, it is compatible and works the same way.

2. Register an account and memories the password, enter your email address or your phone number, then obtain verification code to complete the registry.

-5-

-->Long press on/off button until the indicator light flashes slowly;  
-->Make sure the indicator light is flashing slowly and confirm it in App;  
-->Choose your 2.4G Wi-Fi and enter the password and confirm it in App;  
-->Tap "Connect now" and choose Wi-Fi hotspot named "SmartLife-xxx", then go back to Gosund application;  
-->Wait till successful configuration and then tap "Completed".

-13-



Gosund

### ► Connect with Your Cellphone


Requirements: 2.4GHz Wi-Fi condition at home

For 2.4Ghz Wi-Fi You'll Need to Know:

1. If you only have 5GHz Wi-Fi router, you will not be able to complete the connection.

-6-


2. If you are using a dual Wi-Fi router and it broadcast 2 Wi-Fi signals, make sure that your phone was connected with the 2.4GHz Wi-Fi signal, it should be the Wi-Fi signal that next to "\_5G" .



-7-

3. If you are using a dual Wi-Fi router but it broadcast only 1 Wi-Fi signal, you will have to manage your Wi-Fi router and change the settings to have 2.4GHz Wi-Fi.

---> Choose the "+" symbol,




-8-

A: For Easy Mode Connection- Blue indicator Light Blink Rapidly ( Twice a second ).


---> Confirm that the smart switch is well installed

---> Open Gosund app


---> "Socket"



-9-



### ► Getting to Know Gosund App



-14-

🕒 Set schedule

✍️ Set device names


🕒 Set timer

Note: edit the default names in this interface, for better management.

### ► Create Scenes/Groups

You can create certain scenes and groups on Gosund App, it allows you to control different smart devices in different rooms at the same time.

-15-



-16-

### ► Device Sharing

If you want to give others the permission to control your smart switch, you can authorize that by device sharing function.

Go to the Gosund app

--> Choose the device you want to share

--> Choose Edit Button --> Choose shared devices

--> Add sharing--> Enter his/her Gosund account

--> Search and complete.

-17-

## ► How To Connect with Amazon Alexa

### Requirements:

1. Amazon Alexa Device and Alexa App
2. The Smart Switch connected with Gosund App
3. Gosund App user ID and password.

### Add Gosund as a "Skill" for Alexa

Open Alexa app and choose Skills & Games

-->Search for Gosund


-->ENABLE TO USE

-->Enter the Gosund account


-18-

-->Authorize to use

-->Choose Gosund. And then, the devices you added on will sync to Alexa App. You can also ask Alexa to discover new devices for you in this moment.



-19-




### How to ask Alexa to turn on/off Smart Plug

First you need to set exact name for the plug on Gosund app. If not, Alexa may tell you: "Sorry, I can't find the device

-20-

named xxx..." You can say to Alexa "Alexa, turn on/off bathroom plug", this command will help you to do the work.



-21-

## ► How To Connect with Google Home

After you connected the smart switches with Gosund app successfully, you can start to link them to

### Google Home app:

Open Google Home app and find "Set up device"


-->Click "Works with Google"

-->Search Gosund

-->Enter your Gosund account

-->Authorize to use.

-22-



## ► Trouble Shooting

Q: Why my phone connection failed ?

A: \* You should try both Easy Mode and AP Mode, read page 6-page 14, make sure to follow the guide and try again.

-27-

\* Confirm your home Wi-Fi is 2.4GHz and you entered the correct password during the connection.

\* Remove&Install the smart switch to start again, see what happens. Contact the after sales service for further help if you still have problems with the connection after following the steps above.

Q: Why can't I voice control it with my Alexa/Google?

A: \* Make sure you set up smart switch successfully on Gosund app, and they are working fine.

-28-

\* Make sure you put correct account when you link Gosund as a skill on Alexa/Google App, and you can find it on your skills.

\* Make sure your Alexa/Google device is working fine.

\* Check the device names that you set for this smart switch, it should be non-repetitive and recognizable for voice assistant, Also, please make sure your native language is available for Alexa.

If you still having trouble to voice control our smart switch after followed all

-29-

instructions, do not hesitate to contact us for help.

Q: Do I need to set up the device again if I changed my router?

A: Yes! you must set up the smart switch again if there is any change of the current Wi-Fi status, either you changed your router or your moved the device to a new house. However, you don't need to worry if you are just moving it inside your room, with the same Wi-Fi.

Q: Why does it turns on/off or comes offline surprisingly ?

-30-

A: Check your Wi-Fi status and make sure the electricity is fine.

Check if you've set timer for it. If everything looks alright, just reset the smart switch on your app again and see what happens.


Email to after-sales services if this problem still exists.

### ► Safety Information

This device is for Indoor&Dry condition use only. Make sure the switch electricity is correct for the appliances that you attempt to use with. Do not try to

-31-

After that you will see the smart switch in the home page of Google Home as "Linked to you", but you still haven't set the device name and assign a home or a room for it.



-23-


disassemble this device by yourself, be aware of product damage and safety risks.

Keep away from hot, humidity and other extreme environment. This device meets UL94 V-0 flammability standard.

### ► Warranty

This smart switch is covered by a limited warranty from gosund for the original purchaser that covers the product from defects in workmanship and materials for 24 months from the date of purchase (damages through normal wear and tear,

-32-



-24-

alteration, misuse, neglect, accident, service by anyone other than the authorized service center, or act of God are not included). During the warranty period and upon verification of defects, this product will be replaced when returned with proper proof of purchase.

### ► Contact Us

Friendly reminder: Different App versions may lead to differences in the interfaces, but the description of the function should be the same.

For any inquiries or comments


-33-



Now click the device that "Linked to you" or open "Works with Google" again to manage your linked devices, follow the steps below and set up the device

-25-

names, rooms and home for the smart plug, you won't be able to voice control it before you complete that.



-26-

concerning our products, please send email to: [service@gosund.com](mailto:service@gosund.com). We will try our best to help you.

Manufacturer:  
Shenzhen Gosund Technology Co., Ltd  
Website: [www.gosund.com](http://www.gosund.com)  
Email Support: [service@gosund.com](mailto:service@gosund.com).



402-000-0326 V1.0

-34-