


Wi-Fi Smart Switch

Model: AP-SMT-Breaker02-1CH




1

Parameter:

Input: AC 100-240V 50/60Hz 16A Max
Output: AC 100-240V 50/60Hz 16A Max
Wi-Fi: IEEE 802.11 b/g/n 2.4GHz
Material: PC V0
Size: 41x20x41mm

Checklist before using the device



- Your smart phone or tablet has connected to a 2.4G WiFi with internet.
- You have the correct WiFi password.
- Your smart phone or tablet must have access to APP Store, Google Play.
- Make sure that your router is MAC-open.



2

User Guide

- ① Start with "Smart Life" APP.



- ② Register an Smart Life account.
- ③ If you have Smart Life account, just log in.




3

④ Please wire the device according to the marking on the cover.


ON/OFF operating principle:

The connected appliances work/stop through live wire power on/off. The device must be powered by L and N




Warning: S1 and S2 can only be connected to the two ends of the wall, and cannot be connected to strong power such as zero-fire line.

4.1 The wiring diagram to connect the electrical appliance.



4

4.2 The wiring diagram to connect the light.



- ⑤ Power on after completion of wiring, and the device is turned on by default, Press and hold the button for about 5s seconds until the WiFi blue LED blinks fast.

- ⑥ Enter the App, tap "+" in the upper right of the page to enter network connection page.


5

- ⑦ Please make sure the device's indicator light rapidly flashes (2 times per second) tap to go on to the next step.

- ⑧ Input your WiFi & password.

- ⑨ Name your device.

- ⑩ When the WiFi LED is on , the device is online. Start to control now!



6